

.....[®]
CALRAD
ELECTRONICS

819 N. Highland Ave.
 Los Angeles, CA 90038

Tel (323) 465-2131, Fax (323) 465-3504
 Visit us on the web at www.calrad.com

New Part No.
40-40VH01-SYL
VGA + Stereo Audio
to HDMI Converter



Calrads new 40-40VH01-SYL video converter provides a simple method to allow PC users to show their image not only on their PC's monitor but also on there HD television by converting VGA, RGB+HV into HDMI-HDTV.

The converter also has a selectable dip switch for 3.5mm stereo R/L audio or digital audio for maximum analog or digital audio performance. This audio feature offers solutions for digital entertainment center to conference room presentation, school and corporate training environments. This product converts the VGA signal to HDMI at the resolution of the VGA video source. If the VGA source is set to 480i, 720p or 1080i, 1080p. Then it will convert to HDMI at the same corresponding resolution. 1Ft. Male to Male VGA cable included.

VGA + Audio Conversion to HDMI



Specifications:

Input signal: VGA, 1920 x 1080 max, Analog Stereo Audio or Digital Audio
 Output Signal: HDMI 1.3, supports DVI format, adapter not included
 DC Power: 5Vdc, 500ma
 Size: L - 3.75" x W - 4.75" x H - 1.25"
 Environmental Operating Temperature 0 to +70°c
 Operating Humidity 10% to 85 % RH (no condensation) Storage
 Temperature -10 to +80°c Storage Humidity 5% to 95 % RH (no condensation)

Supported VGA Resolutions:
 VGA 640x480 60Hz, 72Hz, 75hz 85Hz
 800x600 60Hz, 72Hz, 75Hz, 85Hz
 1024x768 60Hz 70Hz, 75Hz, 85Hz
 1280x1024 60Hz, 75Hz, 85Hz
 1600x1200 60Hz
 1920x1080 60Hz